



CounterPath Solutions Inc.

5th Floor, 100 West Pender Street
Vancouver, British Columbia
Canada V6B1R8

Telephone: +1.604.320.3344
www.counterpath.com

**Migration Notes
eyeBeam 1.5**

April, 2006

This document provides guidelines for migrating from eyeBeam 1.1 to eyeBeam 1.5.
Read it to ensure that you do not lose information that may be important to you.

Account Settings

During installation of eyeBeam 1.5, some account settings from eyeBeam 1.1 are migrated, while others are not. Before installing eyeBeam 1.1, make a note of the value for eyeBeam 1.1 settings that will not be migrated, so you can enter them into eyeBeam 1.5 after installation. See Table 1 on page 3.

- To view eyeBeam 1.1 account settings, right-click and choose Settings. The account settings are under SIP Accounts > account name.
- To view eyeBeam 1.5 settings, right-click and choose SIP Account Settings. On the SIP Accounts window, select the account to view and press Properties.

Merging Contact Lists

During installation of eyeBeam 1.5, contacts from the account with the most contacts are migrated; contacts from other accounts are not migrated. In addition, the groups within the largest account are ignored; all contacts are migrated to the “No Group” group .

If you have more than one account, you should move contacts from all accounts into one account. In this way, all your contacts will be migrated.

1. Enable all accounts: right-click, choose Settings, and click “Enable this SIP account” on each account.
2. Open the Calls & Contacts drawer. The contacts for all enabled accounts are shown.
3. Drag all groups into the target account. Do not worry about how the groups look, because the groups will be lost (flattened into one group) when you install eyeBeam 1.5.
4. Install eyeBeam 1.5. Open the Calls & Contacts drawer in eyeBeam 1.5 and organize the contacts into categories as desired. In addition, turn on the “Show this contact's Availability” if you want to see a contact’s availability. See the Contacts List section of the eyeBeam 1.5 User Guide for details.

Migrating Received, Missed and Dialed Calls

During installation of eyeBeam 1.5, all entries in the Calls lists are lost. If you have important phone numbers in these lists that do not have entries in your Contacts lists, deal with them before installing eyeBeam 1.5: set them up as contacts in one account.

Options

During installation of eyeBeam 1.5, none of the eyeBeam 1.1 account settings under Media, System, User Interface or Diagnostics are migrated.

Before installing eyeBeam 1.5, make a note of the value of some eyeBeam 1.1 settings, so you can enter them into eyeBeam 1.5 after installation. See Table 2 on page 5. Note that there are many settings in eyeBeam 1.1 that do not appear in eyeBeam 1.5. Table 2 lists all the settings that are included in eyeBeam 1.5.

- To view eyeBeam 1.1 account settings, right-click and choose Settings. The account settings are under Media, System, User Interface and Diagnostics.
- To view eyeBeam 1.5 settings, right-click and choose Options. These settings apply to eyeBeam in general, not to a specific account.

Table 1: Account Settings Mapping

Migrated	eyeBeam 1.5		eyeBeam 1.1		Comment
	Account Settings Tab	Field	Account Settings Pane	Field	
√	Account	Display name	Server	Display name	
√	Account	User name	Server	User name	
√	Account	Password	Server	Password	
√	Account	Authorization user name	Server	Authorization user name	
√	Account	Domain	Server	Domain	
	Account	Register with domain and receive incoming calls	Server	Register with domain	
√	Account	Send Outbound via	Server	Use as outbound proxy	
√	Account	Address	Server	Manual override	
	Account	SIP Listen Port	Server	SIP Listen Port	
	Account	Address	Server	Address	
	Account	Dialing plan	Advanced	Dialing plan	
	Voicemail	Check for voicemail		not a feature of eyeBeam 1.1	
	Voicemail	Number to dial to check		not a feature of eyeBeam 1.1	
	Voicemail	Number for sending	Advanced	Voicemail URL	
	Voicemail	Forward No Answer		not a feature of eyeBeam 1.1	
	Voicemail	Forward No Answer – seconds		not a feature of eyeBeam 1.1	
	Voicemail	Forward Always checkbox		not a feature of eyeBeam 1.1	
	Voicemail	Forward Always – URI	Advanced	Forward URL	
	Voicemail	Forward Busy checkbox		not a feature of eyeBeam 1.1	
	Voicemail	Forward Busy – URI		not a feature of eyeBeam 1.1	
	Topology	IP Address discovery	Firewall/NAT	Send internal IP	
√	Topology	STUN Server	Firewall/NAT	STUN server	
√	Topology	STUN Server address	Firewall/NAT	STUN server	
√	Topology	Enable ICE	Firewall/NAT	STUN server	
	Topology	Port used on local computer checkbox		not a feature of eyeBeam 1.1	
	Topology	Port used range (2 fields)		not a feature of eyeBeam 1.1	
	Topology	XTunnels Use Xtunnels	XTunnels	Use Xtunnels	
	Topology	XTunnels Use SIP Credentials	XTunnels	Use SIP Credentials	
	Topology	XTunnels SIP credentials - User name	XTunnels	SIP credentials - User name	

Migrated	eyeBeam 1.5		eyeBeam 1.1		Comment
	Account Settings Tab	Field	Account Settings Pane	Field	
	Topology	XTunnels SIP credentials – Password	XTunnels	SIP credentials – Password	
√	Presence	Presence Mode	Presence	Presence Mode	
√	Presence	Presence Poll time (one setting for both modes)	Presence	Poll time (one setting for each of Peer-to-peer and Presence Agent)	
√	Presence	Presence Refresh interval (one setting for both modes)	Presence	Refresh interval (one setting for each of Peer-to-peer and Presence Agent)	
√	Storage	Storage Method	Server-side Storage	Storage Method	
√	Storage	Use SIP credentials	Server-side Storage	Use SIP credentials	
√	Storage	User name	Server-side Storage	User name	
√	Storage	Password	Server-side Storage	Password	
√	Storage	Storage Root URL	Server-side Storage	Storage Root URL	In eyeBeam 1.5, this storage applies to both Presence and Storage
√	Storage	Storage WebDAV poll time	Server-side Storage	Storage WebDAV poll time	
	Security	Signalling Transport	Advanced	Transport	
	Security	Media encryption		not a feature of eyeBeam 1.1	
	Advanced	Reregister every <secs>	Advanced	Reregister every	
	Advanced	Reregister Min /max time	Advanced	Reregister Min/max time	
	Advanced	Send SIP keep-alives	Advanced	Send SIP keep-alives	
	Advanced	Use rport	Advanced	Use rport	
	Advanced	Enable session timers		not a feature of eyeBeam 1.1	
	Advanced	Default session time		not a feature of eyeBeam 1.1	
	Advanced	Session Timers preference		not a feature of eyeBeam 1.1	

Table 2: Options Mapping

eyeBeam 1.5 Option		eyeBeam 1.1 Setting		
Panel	Field	Pane	Subpane	Field
Application	Always on top	User Interface	General	Always on top
	Launch when Windows starts	User Interface	General	Launch when Windows starts
	Prompt when shutdown			not a feature of eyeBeam 1.1
	Turn letter into digits	User Interface	Advanced	Letters-to-digits-mode
	Contact List – double clicking will			not a feature of eyeBeam 1.1
	Recent calls – number of calls	User Interface	General	Number of calls saved on exit
	Zero touch device configuration			not a feature of eyeBeam 1.1
	Zero touch bandwidth detection			not a feature of eyeBeam 1.1
	Enable status bar messages			not a feature of eyeBeam 1.1
	Folder for recording	Media	General	Folder for media files
Alerts	Ring tones import, play, stop, delete, activate			not a feature of eyeBeam 1.1
	Call notification – popup phone			not a feature of eyeBeam 1.1
	Show Call Alerts			not a feature of eyeBeam 1.1
	Instant Message – play alert sound			not a feature of eyeBeam 1.1
Status	Status new/edit/delete	User Interface	Status	Status Message
	Status Auto detect idleness	User Interface	Status	Show me as “Away”
Device	Audio Devices Headset – microphone	Media	Audio >Devices > Headset	Microphone settings – Device Name
	Audio Devices Headset – speaker			In eyeBeam 1.1, the microphone and speaker on the headset are not set separately.
	Audio Devices Headset –use AEC	Media	Audio >Devices > Headset	Microphone settings – enable acoustic echo cancellation
	Audio Devices Headset –use AGC		Audio > General	Automatic Gain Control
	Audio Devices Headset –use noise reduction		Audio > General	Enable microphone noise reduction
	Audio Devices Speakerphone – microphone	Media	Audio >Devices > Speaker Phone	Microphone settings – Device Name
	Audio Devices Speakerphone			In eyeBeam 1.1, the microphone and speaker on the speakerphone are not set separately.

eyeBeam 1.5 Option		eyeBeam 1.1 Setting		
Panel	Field	Pane	Subpane	Field
	Audio Devices Speakerphone - use AEC	Media	Audio > Devices > Speaker Phone	Microphone settings – enable acoustic echo cancellation
	Audio Devices Speakerphone - use AGC	Media	Audio > General	Automatic Gain Control
	Audio Devices Speakerphone - use noise reduction	Media	Audio > General	Enable microphone noise reduction
	Audio Devices Ring device			not a feature of eyeBeam 1.1
	Video Device Camera	Media	Video > General	Camera
Audio Codecs	Audio codec Disabled/Enabled	Media	Audio > Advanced > Codecs	Disabled/Enabled
Video Codecs	Video codec Disabled/Enabled	Media	Audio > Advanced > Codecs	Disabled/Enabled
Network	Speed of network connection			not a feature of eyeBeam 1.1
	Preserve bandwidth	Media	Audio > Devices	Enable VAD
	Call inactivity – hangup	System	Network	Enable RTP inactivity timer
	Call inactivity – seconds	System	Network	Inactivity time
Quality of Service	Audio – type			not supported
	Audio – reserve bandwidth			not supported
	Video – type			not supported
	Signalling – type			not supported
Diagnostics	Enable logging			eyeBeam Logging
	Content to log			eyeBeam Logging
	Log output folder	Diagnostics		Log Output Folder